

# Configure your personal computer to send and receive information using the Iridium 9555 as a Modem with Windows XP

## Installing the USB Drivers

1. Obtain the USB Drivers from SatCom website on <http://www.satcomgroup.com/support/?article=808>
2. Extracted to a well known location e.g. C:\
3. Plug the USB cable from the handset to the PC.
4. When the "Found New Hardware Wizard" find the handset select "No, not this time" > Next
5. Select "Install from a list or specific location (Advanced)" > Next
6. Check the box "Include this location in the search" > Browse
7. Browse to the location where you extracted the drivers in step 2.
8. There will be two folders, please select VCOMPORT > OK
9. Select Next
10. Select "Continue Anyway" for the windows security driver installer
11. Lastly click Finish

## Install the Modem

1. Close all applications.
2. Choose Start > Control Panel.
3. Double click on Phone and Modem Options.
4. Select the Modems tab and click Add...
5. Check "Don't detect my modem; I will select it from a list." Then, click Next >
6. From the Manufacturer list, highlight Standard Modem Types
7. Click Standard 19200 bps Data Modem, and then click Next>.
8. Click the "Selected ports" button. Click on an available COM Port (e.g., COM1). This is the port to which you will connect your Iridium phone. Click Next >.
9. Click Finish.

## Configure Dial-Up Networking

1. Choose Start > All Programs > Accessories > Communications > Network Connections.
2. Click "Create a new connection".
3. Click Next>.
4. Select "Connect to the Internet" and click Next>.
5. Select "Set up my connection manually" and click Next>.
6. Select "Connect using a dial-up modem" and click Next>.
7. If a "Select a Device" window appears, check the box next to "Standard 19200 bps Data Modem", and uncheck all other devices. Click Next>.
8. Enter a connection name (e.g., "Iridium Direct Internet 2.0") and click Next>.
9. In the Phone Number box, enter 008816000025 and click Next>.
10. If using XP Professional Edition, a window may appear to select either "Anyone's use" or "My use only". Choose either selection and click Next>.
11. A username and password are not necessary. Click Next>.
12. Click Finish
13. Click Properties.
14. Click the Networking tab.
15. Make sure "Internet Protocol (TCP/IP)" is checked. Uncheck all other components.
16. Click OK.
17. Close the connection box.