



www.**satellite**-telephone.ch

IRIDIUM DataKit - Setup & Configuration for Windows Vista

During any of the following steps you may be required several times to approve access by Windows UAC (User Account Control). When prompted, choose *Continue*.

Install the Modem

1. Close all applications.
2. Choose *Start > Control Panel*.
3. Double click on *Phone and Modem Options*.
4. Select the *Modems* tab and click *Add...*
5. Check *Don't detect my modem; I will select it from a list*. Then, click *Next >*.
6. From the *Manufacturer* list, highlight *Standard Modem Types*
7. In the right pane click *Standard 19200bps Modem*, and then click *Next>*.
8. Click the *Selected ports* button. Click on an available COM Port (e.g., COM1). This is the port to which you will connect your Iridium device. Click *Next >*.
9. Click *Finish*. Close all windows except *Control Panel*.
10. From *Control Panel* Double Click *Phone and Modem Options*
11. Click *Modems* tab, then *Properties*, then *Change Settings*, then the *Advanced* tab.
12. Add *Initialization String*: AT+CBST=71,0,1 and click *OK*.
13. Modem addition and setup complete. *Close the Phone and Modem Options window*.

Configure Dial-Up Networking

1. Choose *Start > Control Panel* Double Click on *Network and Sharing Center*.
2. Click *Set Up a Connection or Network* (upper left).
3. Choose *Set Up a Dial Up Connection*. Click *Next>*.
4. In the *Dial Up Phone Number* field, type: **008816000025**
5. Leave *User Name and Password* fields blank, In the *Connection Name* field create an appropriate name for the connection (e.g. Iridium Data).
6. Click *Connect* then *Skip* and choose *Set Up The Connection Anyway*. Click *Close*.
7. Return to the *Network and Sharing Center* and choose *Manage Network Connections* (upper left) to initiate call dialing.

Marine-Electronic (INSAM) SA
41, rue Louis-de-Savoie
CH - 1110 Morges
Switzerland

Tel. +4121 8262111
Fax +4121 8262114
Mobile +4179 2102170
info@marine-electronic.com